Get an Ultra-Slim USB Stick

DeadDrop Ready

Written By: Aaron Soehnen

⚒ TOOLS:

- [Hot Glue gun & hot glue (1)](#)
- [Soldering iron (1)](#)
- [Wire cutter/stripper (1)](#)

⚙ PARTS:

- [Slim USB Stick (1)](#)

SUMMARY

First of all: If you're not familiar with DeadDrops, visit [deaddrops.com](#)!

You surely know these new type of USB sticks which are very thin because they don't have the classic-iron USB connector. I had a bunch of them at home and wanted to use them as DeadDrops, but in my opinion the plastic connector is not solid enough for a DeadDrop's life of rain, physical stress, and vandalism. I solved this problem by soldering an end of an USB cable to them. I think that's really easy, so get your slim USB stick and an old cable or connector and get started!

Step 1 — Get an Ultra-Slim USB Stick DeadDrop Ready

- **What you'll need:**

- A slim USB stick

- A male USB connector with or without a cable

- Soldering iron

- A pair of scissors or any kind of nipper pliers

- Hot glue (optional)

- Heat-shrink tubing

- And some plumber's tape or any kind of waterproof tape (not in the image)

Step 2

- If your stick has got any kind of a non-solid plastic casing, remove it.

- Removing the plastics can be done using a knife, a screwdriver or a Dremel-kind-of-tool.

- You should end up having the circuit board (as in my case) or the elemental plastic part with the connectors.

- *Be sure that you are opening only the outer plastic casing and **not** the inner one!*

Step 3

- To get ready for soldering, you have to prepare your USB cable / USB male connector first.

- **If you are using a cable end:**

  - Gently remove about 1-2 cm of the outer plastic insulation of the cable.

  - Remove the tinfoil shielding by peeling it back and cutting it off. (Sometimes the shielding consists of many small wires. Don't worry, cut 'em off too!)

  - Now strip the four colored wires.

- **If you are using a male connector:**

  - Remove any plastics that are covering the inner parts of your connector using a knife.

Step 4

Based on the .svg by Simon A. Eugster

- Now it is time to solder the USB stick and the connector or wire together.

- Be sure to solder the connections right and stick to the image if in doubt. (Oh, and sometimes the green wire is blue.)

Step 5

- If you like you can use heat-shrink tubing and/or hot glue to secure the solder connections.

- After that you just have to wrap the finished USB stick with some tape to make it waterproof and you're done!

- A finished Dead Drop can be seen here at the Dead Drops Database

This document was last generated on 2012-11-03 04:05:25 AM.